


```
float c;
bool d;
} struct_message;

// Creation d une structure de message appelée myData
struct_message myData;

esp_now_peer_info_t peerInfo;

// Retour de message de status l'autre esp
void OnDataSent(const uint8_t *mac_addr, esp_now_send_status_t status)
{
    Serial.print("\r\nLast Packet Send Status:\t");
    Serial.println(status == ESP_NOW_SEND_SUCCESS ? "Bouton OK" : "Erreur
Bouton");
}

void setup() {

    Serial.begin(115200);

    pinMode(Bp1, INPUT);

    WiFi.mode(WIFI_STA);

    // Initiation ESP-NOW
    if (esp_now_init() != ESP_OK) {
        Serial.println("Error initializing ESP-NOW");
        return;
    }

    //Recupere le status du paquet envoyer
    esp_now_register_send_cb(OnDataSent);

    // test l'adress Mac , Envoi sur canal 0, et ne pas crypter le paquer
    memcpy(peerInfo.peer_addr, broadcastAddress, 6);
    peerInfo.channel = 0;
    peerInfo.encrypt = false;

    if (esp_now_add_peer(&peerInfo) != ESP_OK){
        Serial.println("Failed to add peer");
        return;
    }
}
```

```
    }  
}  
  
void loop() {  
    int valeurBp1 = digitalRead(Bp1); // On lit la valeur de Bp1 au début  
    de la boucle  
    delay(tempo);  
  
    strcpy(myData.a, " data1");  
    myData.b = 0;  
    myData.c = 0.5;  
  
    //Temps 1  
    if (valeurBp1 == 1 && MemBp1 == 0 && MemLed1 == 0) {  
        myData.d = 1;; MemBp1 = 1; MemLed1 = 1;  
        esp_err_t result = esp_now_send(broadcastAddress, (uint8_t *)  
&myData, sizeof(myData));  
    }  
    //Temps 2  
    if (valeurBp1 == 0 && MemBp1 == 1 && MemLed1 == 1) {  
        myData.d = 1;; MemBp1 = 0; MemLed1 = 1;  
    }  
    //Temps 3  
    if (valeurBp1 == 1 && MemBp1 == 0 && MemLed1 == 1) {  
        myData.d = 0;; MemBp1 = 1; MemLed1 = 0;  
    }  
    //Temps 4  
    if (valeurBp1 == 0 && MemBp1 == 1 && MemLed1 == 0) {  
        myData.d = 0;; MemBp1 = 0; MemLed1 = 0;  
        esp_err_t result = esp_now_send(broadcastAddress, (uint8_t *)  
&myData, sizeof(myData));  
    }  
  
    Serial.println(myData.d); // affiche la valeur envoyée mydata.d ==>  
    booleen  
  
    if (result == ESP_OK) {  
        Serial.println("Sent with success");  
    }  
    if (result == " "){  
        Serial.println("Attente d'appui !!!");  
    }  
    else {  
        Serial.println("Error sending the data");  
    }  
    delay(1000);  
}
```

Recepteur avec Led

recepteur001.ino

```
/*
   Raccorder la led sur la sortie 2
*/

#include <esp_now.h>
#include <WiFi.h>

int led1 = 2;
int tempo = 50;

// Structure example to receive data
// Must match the sender structure
typedef struct struct_message {
    char a[32];
    int b;
    float c;
    bool d;
} struct_message;

// Create a struct_message called myData
struct_message myData;

// callback function that will be executed when data is received
void OnDataRecv(const uint8_t * mac, const uint8_t *incomingData, int len) {
    memcpy(&myData, incomingData, sizeof(myData));
    Serial.print("Bytes received: ");
    Serial.println(len);
    Serial.print("Char: ");
    Serial.println(myData.a);
    Serial.print("Int: ");
    Serial.println(myData.b);
    Serial.print("Float: ");
    Serial.println(myData.c);
    Serial.print("Bool: ");
    Serial.println(myData.d);
    Serial.println();
}

void setup() {
    // Initialize Serial Monitor
    Serial.begin(115200);
    pinMode(led1, OUTPUT);

    // Set device as a Wi-Fi Station
```

```
WiFi.mode(WIFI_STA);

// Init ESP-NOW
if (esp_now_init() != ESP_OK) {
  Serial.println("Error initializing ESP-NOW");
  return;
}

void loop() {
  esp_now_register_recv_cb(esp_now_recv_cb_t(OnDataRecv));
  delay(1000);

  if (myData.d == true) {
    digitalWrite(led1, HIGH);
  }
  if (myData.d == false) {
    digitalWrite(led1, LOW);
  }
}
```

From:

<https://chanterie37.fr/fablab37110/> - Castel'Lab le Fablab MJC de Château-Renault

Permanent link:

<https://chanterie37.fr/fablab37110/doku.php?id=start:arduino:esp32:tp:now&rev=1730971144>

Last update: **2024/11/07 10:19**

